

Veritas 1100BH

smart mixer amplifier



Product Overview

The award-winning Veritas series from Bose Professional delivers superior background/foreground music, paging and multimedia for commercial applications. *Bluetooth*® 5.0 wireless input and user-intuitive OLED screen with quick-start QR code simplify setup—whether you're a pro installer or a DIYer. With four models to choose from, Veritas amplifiers offer the perfect combination of power, performance and flexibility.

Compact and powerful, the 1100BH is suited for smaller distributed audio systems, background music, and paging applications. Designed for 70V/100V high-impedance systems, it efficiently powers multiple wall or ceiling loudspeakers to deliver broad coverage. Perfect for smaller venues, offices, and retail spaces, the 1100BH features a smaller half-rack size and front XLR/¼-inch input for convenient mic or audio source connection.

Key Features

- Premium amplification** with advanced DSP for optimized performance
- Bluetooth connectivity** and RCA connectivity—no wire splicing required
- Intuitive front-panel OLED screen** for easy setup and control
- Included bracket accessory** for mount-anywhere flexibility
- Embedded quick-start QR code** in the OLED screen simplifies installation
- Supports high-impedance** (70/100V) applications
- Remote level control** with Bose Professional or third-party wall controllers
- Dynamic EQ** adjusts bass levels to achieve a fuller sound even at low volumes
- Up to 30 selectable EQ presets** ensure Bose Professional signature sound performance and long-term reliability
- Opti-Voice** paging feature ensures clear speech intelligibility
- Convection cooling** for fanless operation in quiet installs such as offices and conference rooms

Applications

- Retail stores
- Restaurants and bars
- Hospitality venues
- Conference centers
- Schools
- Auxiliary zones

Veritas 1100BH

smart mixer amplifier

Technical Specifications

POWER RATING		
Amplifier Power	1 × 100 W at 70V/100V	
AUDIO PERFORMANCE		
Frequency Response	70 Hz – 18 kHz (+0/-4 dB, @ 1 W reference 1 kHz)	
THD+N	≤0.3 % (at full rated power)	
Channel Separation (Crosstalk)	n/a	
Dynamic Range	88 dB	
INTEGRATED DSP		
A/D & D/A Converters	24-bit, 48 kHz	
Processing Functions	Loudspeaker EQ, Opti-Voice paging, Dynamic EQ	
Loudspeaker Presets	70 Hz high-pass filter, 80 Hz high-pass filter, AMU105, AMU108, DesignMax (all models), EdgeMax (all models), FreeSpace FS (all models), subwoofer	
Audio Latency	10.4 ms (any input to speaker output or aux output)	
AUDIO INPUTS	Line Inputs	Page Inputs
Input Channels	(2) unbalanced line, (1) balanced mic/line	(1) balanced mic/line
Connectors	(2) RCA stereo pairs, (1) XLR/¼-in	(1) 4-pin Euroblock
Adjustment Range	-20 dB to +20 dB	0 dB to +50 dB
Input Impedance	20 kΩ	2.4 kΩ
Maximum Input Level	+10 dBV	+10 dBV
Sensitivity	-10 dBV	-58 dBV
Nominal Input Level	0 dBV	-40 dBV
AUDIO OUTPUTS	Loudspeaker Outputs	Auxiliary Outputs
Output Channels	(2) loudspeaker	(1) unbalanced line
Connectors	(1) 3-pin inverted Euroblock	(1) RCA stereo pair
Output Impedance	n/a	400 Ω
Nominal Output Level	1 × 100 W at 70V/100 V	0 dBV (max)
INDICATORS & CONTROLS		
Power LED	Solid blue (powered on)	
Input Clip LED	Green (-34 dBu to +10 dBu), red (> +10 dBu). Input gain level set to 5.	
Bluetooth LED	Off (no <i>Bluetooth</i> device connected), blinking blue (ready to pair to a <i>Bluetooth</i> device), solid blue (connected to a <i>Bluetooth</i> device)	
Display	OLED, 16-bit grayscale, 96 × 96 resolution	
Controls, Front Panel	Power on/off switch, input select switch (A/ <i>Bluetooth</i> /B), input gain knob (XLR/¼-in), rotary encoder	
Controls, Rear Panel	Input gain knobs (A, B, page), mute connector, ControlCenter port	

Veritas 1100BH

smart mixer amplifier

ELECTRICAL	
Mains Voltage	100 VAC – 240 VAC (±10%, 50/60 Hz)
AC Power Consumption	15 W idle, 200 W maximum
Mains Connector	Standard IEC (C14)
Overload Protection	High temperature, output short
PHYSICAL	
Cooling System	Natural convection
Product Dimensions (height × width × depth)	44 mm × 214 mm × 310 mm (1.7 in × 8.4 in × 12.2 in)
Net Weight	3.2 kg (7.1 lb)
Package Contents	(1) Veritas 1100BH, (2) mounting brackets, (6) screws, (4) mounting feet with pins, (1) 4-pin Euroblock connector, (1) 3-pin Euroblock connector, (1) 2-pin Euroblock connector, (1) power cord, (1) installation guide
Optional Accessories	Rack mounting kit, ControlCenter CC-1, ControlCenter CC-2
PRODUCT CODES	
Veritas 1100BH, 120 V, US	892237-1110 VERITAS 1100BH 120V US
Veritas 1100BH, 230 V, EU	892237-2110 VERITAS 1100BH 230V EU
Veritas 1100BH, 230 V, UK	892237-4110 VERITAS 1100BH 230V UK
Veritas 1100BH, 100 V, JP	892237-3140 VERITAS 1100BH 100V JP
Veritas 1100BH, 230 V, CN	892237-2140 VERITAS 1100BH 230V CN
Veritas 1100BH, 240 V, AU	892237-5110 VERITAS 1100BH 240V AU
Rack mounting kit	892122-0100 VERITAS AMP RACK MOUNT KIT BLACK
ControlCenter CC-1, US, black	768932-0110 CONTROLCENTER CC-1 US BLACK
ControlCenter CC-1, US, white	768932-0210 CONTROLCENTER CC-1 US WHITE
ControlCenter CC-1, EU, black	768932-2110 CONTROLCENTER CC-1 EU BLACK
ControlCenter CC-1, EU, white	768932-2210 CONTROLCENTER CC-1 EU WHITE
ControlCenter CC-1, JP, black	768932-3110 CONTROLCENTER CC-1 JP BLACK
ControlCenter CC-1, JP, white	768932-3210 CONTROLCENTER CC-1 JP WHITE
ControlCenter CC-2, US, black	768938-0110 CONTROLCENTER CC-2 US BLACK
ControlCenter CC-2, US, white	768938-0210 CONTROLCENTER CC-2 US WHITE
ControlCenter CC-2, EU, black	768938-2110 CONTROLCENTER CC-2 EU BLACK
ControlCenter CC-2, EU, white	768938-2210 CONTROLCENTER CC-2 EU WHITE
ControlCenter CC-2, JP, black	768938-3110 CONTROLCENTER CC-2 JP BLACK
ControlCenter CC-2, JP, white	768938-3210 CONTROLCENTER CC-2 JP WHITE

Veritas 1100BH

smart mixer amplifier

Hardware Details



1. **Power switch:** Turns amplifier on or off.
2. **Power LED:** Illuminates blue when amplifier is on.
3. **Input/clip LED:** Illuminates red whenever input source approaches the threshold value of +10 dBu. If the indicator illuminates frequently, reduce input signal level.
4. **Mic/line input:** XLR/¼ TRS combo jack for connecting a dynamic microphone.
5. **Gain knob:** Allows for fine-tuning of the mic/line input level. If the input/clip indicator is red, reduce the input gain. The adjustment range is 0 dB to +50 dB.
6. **Bluetooth LED:** LED is off when no device is connected to *Bluetooth* technology. LED blinks blue when ready to pair with a *Bluetooth*-enabled device. LED is solid blue when a *Bluetooth* enabled device is connected.
7. **Input selection switch:** Allows you to choose between rear line inputs A/*Bluetooth* and B from the front panel of the amplifier.
8. **Display:** 16-bit grayscale OLED display, 96 × 96 resolution.
9. **Rotary encoder:** Controls the menu interface as well as adjusts volume, bass, and treble levels.



1. **Line input:** Unbalanced line-level input connectors (processed as stereo signals).
2. **Gain knob:** Allows for -20 dB to +20 dB of adjustment to each Input A/B. Allows for 0 dB to +50 dB of gain control of page input signal.
3. **Page input:** Euroblock mic/line input that supports dynamic microphones with a trigger contact closure for use with push-to-talk (PTT) microphones.
4. **Aux output:** Variable or fixed, unbalanced line-level output signal for routing the signal to additional audio equipment.
5. **Mute connector:** Contact closure connection that upon trigger will mute all outputs (including aux output).
6. **Update port:** USB-C port for software updates.
7. **ControlCenter port:** Input connector for either a CC-2 zone controller for volume control and A/B source selection or a CC-1 zone controller for volume control only.
8. **Loudspeaker output:** Inverted 3-pin Euroblock connectors for 70V/100V loudspeaker connections.
9. **Power input:** Standard IEC power cord receptacle.

© 2024 Transom Post OpCo LLC. All rights reserved. Bose is a trademark of Bose Corporation. The *Bluetooth*® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Bose Professional is under license. All other trademarks are the property of their respective owners.

For additional specifications and application information, visit BoseProfessional.com. Specifications are subject to change. 04/2025